

SPECIFICATION SHEET
JFW MODEL 50SA-509
SOLID-STATE SWITCH ASSEMBLY

JFW Industries, Inc.
 Phone: 317-887-1340
 sales@jfwindustries.com
 www.jfwindustries.com

Frequency Range	700-3000 MHz
Configuration	1P12T self-terminating solid-state RF switch
Indicators	LED's on front panel denote active port
Enclosure Type	19 inch rack mount @ 1RU high
Startup/Default States (configurable)	RF switch off at startup (see SWITCH command) DHCP enabled (see NET command) 4 Ethernet users (see NET command) Prompts off (see PROMPT command)
Impedance	50 Ohms nominal
VSWR	1.6:1 maximum
Insertion Loss	4.0 dB maximum 2.0 dB typical @ 700 MHz 3.3 dB typical @ 3000 MHz
Isolation	60 dB minimum
RF Input Power	+30 dBm
Switching Speed	20 microseconds (after command is received and processed) (3 milliseconds typical processing time)
Control	Ethernet (DHCP, TCP/IP, 10/100, up to 12 users) RS-232 (up to 115200 Baud)
Remote Command Format	RF Switch Control Commands: Switch, Set Switch, Read Switch System Commands: Help, Identification, Store, Recall, Pause, Net, Serial, Close, Disconnect, MOTD, Date, Message, Restrict, IDENT, Name, Show Users, Reboot, Uptime, Prompt
AC Supply	100-240 VAC @ 47-63 Hz 2 Amp 5x20mm "Slo-Blo" AC fuse Littelfuse #215-002, JFW #025-021
RF Connectors	SMA female
Operating Temperature Range	0° to +50°C
Physical Size	See outline drawing 092-8323

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	05/26/2015		TRS 05/26/2015				