

SPECIFICATION SHEET**JFW MODEL 50S-1316+XX****1P6T NORMALLY OPENED ELECTROMECHANICAL RF SWITCH**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-18 GHz
Configuration	1P6T Normally Open
Impedance	50 Ohms nominal
VSWR	1.2:1 maximum DC-4GHz 1.3:1 maximum 4-8GHz 1.4:1 maximum 8-12GHz 1.5:1 maximum 12-18GHz
Insertion Loss	0.2 dB maximum DC-4GHz 0.3 dB maximum 4-8GHz 0.4 dB maximum 8-12GHz 0.5 dB maximum 12-18GHz
Isolation	70 dB minimum DC-4GHz 65 dB minimum 4-8GHz 60 dB minimum 8-12GHz 60 dB minimum 12-18GHz
Switching Speed	20 milliseconds
RF Input Power	400 Watts average DC-200MHZ 300 Watts average 200-500MHZ 200 Watts average 500-1000MHZ 100 Watts average 1-4GHZ 90 Watts average 4-8GHZ 70 Watts average 8-12GHZ 60 Watts average 12-18GHZ
Control (6 lines)	+XX is either +12, +15 or +28: ----- +12 Vdc @ 325 mA nominal +15 Vdc @ 280 mA nominal +28 Vdc @ 160 mA nominal on control line corresponding to desired port.(Only one active port at a time.)
Lifetime	1 million cycles minimum
Weight	4 oz. Nominal
DC Connector	Solder Terminals
RF Connector	SMA female

--CONTINUED--

SPECIFICATION SHEET

JFW MODEL 50S-1316+XX

1P6T NORMALLY OPENED ELECTROMECHANICAL RF SWITCH

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Operating Temperature Range -20°C to +65°C

Physical Size See outline drawing 092-4187



ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	08/18/2005		BAC 08/18/2005				
14089	04/19/2007	A	BAC 04/19/2007				