

**SPECIFICATION SHEET**

**JFW MODEL 57ZTT-AA AND 75ZTT-AA  
IMPEDANCE MATCHING TRANSFORMER**

JFW Industries, Inc.  
Phone: 317-887-1340  
sales@jfwindustries.com  
www.jfwindustries.com

Frequency Range 800-2200 MHz

Impedance 57ZTT-AA: 50 Ohm male  
75 Ohm female

75ZTT-AA: 75 Ohm male  
50 Ohm female

VSWR 1.3:1 maximum

Insertion Loss 0.5 dB maximum

RF Input Power 20 Watts average

RF Connector BNC, N or F (75 Ohm side)  
BNC, N or SMA (50 Ohm side)

Operating Temperature Range -55°C to +85°C

Physical Size See outline drawing  
092-3179 (57ZTT-AA N M/F)  
092-6023 (57ZTT-AA SMA M/F F)  
092-3183 (75ZTT-AA N M/F)  
092-3313 (75ZTT-AA N M/S F)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	04/01/1999			9999	02/17/2004	C	SL 02/17/2004
2209	10/12/1999	A		16611	12/12/2008	D	SMR 12/12/2008
3050	07/16/2002	B					