

SPECIFICATION SHEET

JFW MODEL 50T-315

TERMINATION

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Description	Termination with Bead Chain
Frequency Range	DC-18 GHz
Impedance	50 Ohms nominal
VSWR	1.1:1 maximum DC-4 GHz 1.2:1 maximum 4-12.4 GHz 1.25:1 maximum 12.4-18 GHz
RF Input Power	1 Watt average @ +25°C Derate to 0 Watts @ +125°C
Peak Power	500 Watts
RF Connector	SMA male with bead chain
Operating Temperature Range	-55°C to +125°C
Physical Size	See outline drawing 092-3986

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	02/10/2000			26049	12/17/2015	C	TRS 12/17/2015
3052	07/17/2002	A		27303	11/29/2016	D	TRS 11/29/2016
9999	02/24/2003	B	SL 06/30/2003				