

SPECIFICATION SHEET

JFW MODEL 50PD-133

2 WAY RESISTIVE POWER DIVIDER

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	DC-2000 MHz
Impedance	50 Ohms nominal
VSWR	1.2:1 maximum to 500 MHz 1.3:1 maximum to 1000 MHz 1.4:1 maximum to 2000 MHz
Insertion Loss	6 dB ± 0.5 dB
Amplitude Tracking	± 0.3 dB
RF Input Power	2 Watts average @ 25°C 100 Watts peak (1 microsecond)
Operating Temperature Range	-40°C to +85°C
RF Connector	N, TNC, or BNC (male or female)
Physical Size	See outline drawing 092-2328 (N F) 092-3921 (NF/NM-2) 092-5297 (BF/NF-2)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
867	10/28/1997	A		2965	04/19/2002	D	
2433	07/20/2000	B		9999	11/16/2002	E	SL 11/27/2002
2948	04/08/2002	C		13794	01/24/2007	F	TRS 01/24/2007