

SPECIFICATION SHEET
JFW MODEL 50PDA-040
POWER DIVIDER ASSEMBLY

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Frequency Range	800-3000 MHz
Configuration	24 way power divider/combiner assembly
Impedance	50 Ohms nominal
VSWR	1.6:1 maximum
Insertion Loss (above 13.8 dB split)	1.9 dB maximum
Isolation	20 dB minimum
Amplitude Tracking	± 0.9 dB
Phase Tracking	± 10°
RF Input Power (common port)	5 Watts average
RF Connector	N female
Operating Temperature Range	-40°C to +85°C
Physical Size	See outline drawing 092-4358

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	12/18/2003		SL 12/18/2003				