

**SPECIFICATION SHEET**  
**JFW MODEL 57Z AND 75Z**  
**IMPEDANCE MATCHING PAD**

JFW Industries, Inc.  
 Phone: 317-887-1340  
 sales@jfwindustries.com  
 www.jfwindustries.com

Frequency Range	DC-1000 MHz
Impedance	57Z    50 Ohm male 75 Ohm female
	75Z    75 Ohm male 50 Ohm female
VSWR	1.2:1 maximum
Attenuation Loss	5.7 dB ± 0.5 dB
RF Input Power	1 Watt average 1000 Watts peak
RF Connector	50 Ohm end - N, N M RT, BNC, TNC or SMA 75 Ohm end - N, BNC, TNC, F or BNC panel mount
Operating Temperature Range	-20°C to +85°C
Physical Size	See outline drawing: 092-004 (BNC M / BNC F) 092-164 (N M / N F) 092-1903 (N M /BNC F) 092-3998 (N F / N F) 092-701 (SMA F / BNC F PM) 092-4282 (SMA F / F F) 092-1360 (SMA M / BNC F) 092-180 (TNC M / TNC F) 092-4861 (N M RT/ N F)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
35	09/22/1992	A		11483	07/13/2005	D	BAC 07/13/2005
2231	11/12/1999	B					
4459	02/06/2004	C	CLV 02/06/2004				